

Promote™ +

Cardiac Resynchronisation Therapy Defibrillator (CRT-D)

Product Highlights

- The DF4 connector is designed to simplify implants by streamlining defibrillation connections into a single terminal pin and reducing the number of set screws
- Triple redundancy safety platform is designed to minimise risk and increase security and patient comfort through multiple hardware and software system safeguards
- Triggered pacing with BiV™ Trigger Mode helps maintain a high percentage of BiV pacing by triggering pacing in both the left and right ventricles in response to a sensed ventricular event
- Negative AV hysteresis with search promotes ventricular pacing by automatically reducing the AV delay when intrinsic activity is present, thereby promoting a high degree of ventricular pacing
- AT/AF Alerts can be programmed to notify patients and their clinics when a programmed AT/AF threshold or continuous episode duration has been exceeded, or when a high ventricular rate accompanies the AT/AF episode
- Vibratory patient notifier enables patients with hearing problems to be alerted to a low battery, lead-related complications and more
- QuickOpt™ timing cycle optimisation provides quick and effective optimisation for more patients at the push of a button
- VectSelect™ programmable LV pulse configuration (LV ring-RV coil, LV tip-RV coil or LV bipolar) may be adjusted noninvasively via the programmer
- DeFT Response™ technology tools provide more clinically proven, noninvasive options for managing high DFTs



Merlin@home™
Transmitter
Compatible

Ordering Information

Contents: Cardiac pulse generator

Model Number	Dimensions (H x W x T, mm)	Weight (g)	Volume (cc)	Connector Defibrillation	Connector Sense/Pace
CD3211-36	81 x 50 x 14	82	43	DF1	IS-1
CD3211-36Q	75 x 50 x 14	82	42	DF4	IS-1; DF4

Indications: The devices are intended to provide ventricular antitachycardia pacing and ventricular defibrillation for automated treatment of life-threatening ventricular arrhythmias. Cardiac Resynchronisation Therapy Defibrillators (CRT-Ds) are also intended to resynchronise the right and left ventricles in patients with congestive heart failure.

Contraindications: Contraindications for use of the pulse generator system include ventricular tachyarrhythmias resulting from transient or correctable factors such as drug toxicity, electrolyte imbalance or acute myocardial infarction.

Adverse Events:

Implantation of the pulse generator system, like that of any other device, involves risks, some possibly life-threatening. These include but are not limited to the following: acute hemorrhage/bleeding, air emboli, arrhythmia acceleration, cardiac or venous perforation, cardiogenic shock, cyst formation, erosion,

exacerbation of heart failure, extrusion, fibrotic tissue growth, fluid accumulation, hematoma formation, histotoxic reactions, infection, keloid formation, myocardial irritability, nerve damage, pneumothorax, thromboemboli, venous occlusion. Other possible adverse effects include mortality due to: component failure, device-programmer communication failure, lead abrasion, lead dislodgment or poor lead placement, lead fracture, inability to defibrillate, inhibited therapy for a ventricular tachycardia, interruption of function due to electrical or magnetic interference, shunting of energy from defibrillation paddles, system failure due to ionising radiation. Other possible adverse effects include mortality due to inappropriate delivery of therapy caused by: multiple counting of cardiac events including T waves, P waves or supplemental pacemaker stimuli. Among the psychological effects of device implantation are imagined pulsing, dependency, fear of inappropriate pulsing and fear of losing pulse capability.

Refer to the User's Manual for detailed indications, contraindications, warnings, precautions and potential adverse events.

Customer Support: 46-8-474-4756

Brief Summary: Prior to using these devices, please review the Instructions for Use for a complete listing of indications, contraindications, warnings, precautions, potential adverse events and directions for use. Devices depicted may not be available in all countries. Check with your St. Jude Medical representative for product availability in your country. Unless otherwise noted, ™ indicates that the name is a trademark of, or licensed to, St. Jude Medical or one of its subsidiaries. ST. JUDE MEDICAL, the nine-squares symbol and MORE CONTROL. LESS RISK. are registered and unregistered trademarks and service marks of St. Jude Medical, Inc. and its related companies. ©2011 St. Jude Medical, Inc. All rights reserved.

Promote™ +

Cardiac Resynchronisation Therapy Defibrillator (CRT-D)

Product Specifications

PHYSICAL SPECIFICATIONS		
Models	CD3211-36	CD3211-36Q
Telemetry	RF	RF
Delivered/Stored Energy (J)	36/42	36/42
Volume (cc)	43	42
Weight (g)	82	82
Size (mm)	81 x 50 x 14	75 x 50 x 14
Defibrillation Lead Connections	DF1	DF4
Sense/Pace Lead Connections	IS-1	IS-1, DF4
High-Voltage Can	Electrically active titanium can	Electrically active titanium can
PARAMETER SETTINGS		
Biventricular Pacing		
V. Triggering (BiV™ Trigger Mode)	On; Off	
QuickOpt™ Timing Cycle Optimisation	Sensed/paced AV delay; Interventricular Pace delay	
V-V Timing	Simultaneous*; RV First; LV First	
Interventricular Pace Delay (ms)	RV First 10-80 / LV First 15-80 in increments of 5	
Ventricular Sensing	RV only (not programmable)	
Ventricular Pacing Chamber	RV only; biventricular	
Negative AV Hysteresis/Search (ms)	Off; -10 to -120	
Shortest AV Delay (ms)	25-120	
VectSelect™ LV Pulse Configuration	LV tip to RV coil; LV bipolar; LV ring to RV coil	
AF Management		
AF Suppression™ Pacing	On; Off	
No. of Overdrive Pacing Cycles	15-40 in steps of 5	
Maximum AF Suppression Rate	80-150 min ⁻¹	
Sensing/Detection		
SenseAbility™ Technology	Automatic Sensitivity Control adjustment for atrial and ventricular events	
Threshold Start	(Post-Sensed; Atrial) 50; 62.5; 75; 100%; (Post-Paced; Atrial) 0.2-3.0 mV; (Post-Sensed; Ventricular) 50; 62.5; 75; 100%; (Post-Paced; Ventricular) Auto; 0.2-3.0 mV	
Decay Delay	(Post-Sensed/Post-Paced; Atrial/Ventricular) 0-220; (Post-Paced Ventricular), Auto	
Ventricular Sense Refractory (ms)	125; 157	
Detection Zones	VT-1; VT-2; VF	
SVT Discriminators	AV Rate Branch; Sudden Onset; Interval Stability; Morphology Discrimination (MD) with Manual or Automatic Template Update	
Reconfirmation	Continuous sensing during charging	
Antitachycardia Pacing Therapy		
ATP Configurations	Ramp; Burst; Scan; 1 or 2 schemes per zone	
Burst Cycle Length	Readaptive or Fixed	
Min. Burst Cycle Length (ms)	150-400 in increments of 5	
Number of Bursts/Stimuli	1-15 with 2-20 Stimuli	
Add Stimuli per Burst	On; Off	
High-Voltage Therapy		
High-Voltage Output Mode	Fixed Pulse Width; Fixed Tilt	
Waveform	Biphasic; Monophasic	
RV Polarity	Cathode (-); Anode (+)	
Electrode Configuration	RV to Can; RV to SVC/Can	
Bradycardia Pacing		
Permanent Modes	Off; DDD(R); DDT(R); DDI(R); VVT(R); VVI(R); AAI(R); DOO(R); VOO(R); AOO(R)	
Temporary Modes	Off; DDD(R); DDT(R); DDI(R); VVT(R); VVI(R); AAI(R); AAT(R); DOO; VOO; AOO	
Rate-Adaptive Sensor	On; Off; Passive	
Programmable Rate and Delay Parameters	Off; Base Rate (min ⁻¹); Rest Rate (min ⁻¹); Maximum Tracking Rate (min ⁻¹); Maximum Sensor Rate (min ⁻¹); Paced AV Delay (ms); Sensed AV Delay (ms); Rate Responsive AV Delay; Pulse Amplitude (Atrial; RV and LV) (V); Pulse Width (Atrial; RV and LV) (ms); Hysteresis Rate (min ⁻¹); Rate Hysteresis with Search	
Auto Mode Switch (AMS)	Off; DDI(R); DDT(R); VVI(R); VVT(R)	
Atrial Tachycardia Detection Rate (min ⁻¹)	110-300	
AMS Base Rate (min ⁻¹)	40; 45; ... 135	
Auto PMT Detection/Termination	Atrial Pace; Off; Passive	
Rate Responsive PVARP/VREF	Off; Low; Medium; High	
Ventricular Intrinsic Preference (VIP™)	Off; 50-200 (50-150 in increments of 25; 160-200 in increments of 10)	

Post-Therapy Pacing (independently programmable from Bradycardia and ATP)

Post-Shock Pacing Mode	Off; AAI; VVI; DDI; or DDD
Post-Shock Base Rate (min ⁻¹)	30-100 in increments of 5
Post-Shock Pacing Duration (min)	Off; 0.5; 1; 2.5; 5; 7.5; or 10

Device Testing/Induction Methods

DC Fibber™ Pulse Duration (sec)	0.5-5.0
Burst Fibber Cycle Length (ms)	20-100
Noninvasive Programmed Stimulation (NIPS)	2-25 stimuli with up to 3 extrastimuli

Patient Notifiers

Programmable Notifiers (On; Off)	Device at ERI; Charge Time Limit Reached; Possible HV Circuit Damage; Atrial Lead Impedance Out of Range; RV Lead Impedance Out of Range; LV Lead Impedance Out of Range; High-Voltage Lead Impedance Out of Range; AT/AF Burden; V Rate During AT/AF; Backup VVI; Long AT/AF Episode
----------------------------------	---

Device Parameter Reset	On
Entry into Backup VVI Mode	On
Vibration Duration (sec)	2; 4; 6; 8; 10; 12; 14; 16
Number of Vibrations per Notification	2
Number of Notifications	1-16
Time Between Notifications (hours)	10; 22

Electrograms and Diagnostics

Stored Electrograms	Up to 45 minutes including up to 1 minute programmable pre-trigger data per VT/VF diagnosis/detection electrograms; triggers include: diagnosis; therapy; atrial episode; PMT termination; PC shock delivery; noise reversion; magnet reversion; and morphology template verification
Therapy Summary	Diagram of therapies delivered
Episodes Summary	Directory listing of up to 60 episodes with access to more details including stored electrograms
Lifetime Diagnostics	History of bradycardia events and device-initiated charging
AT/AF Burden Trend	Trend data and counts
Ventricular HV Lead Impedance Trend Histograms	Multi-Vector Trend Data Event Histogram; AV Interval Histogram; Mode Switch Duration Histogram; Peak Filtered Rate Histogram; Atrial Heart Rate Histogram; Ventricular Heart Rate Histogram; AT/AF Burden; Exercise and Activity Trending; V Rates During AMS
PMT Data	Information regarding PMT detections
Real-Time Measurements (RTM)	Pacing lead impedances; high-voltage lead impedances; unloaded battery voltage; and signal amplitudes

*LV first with 10 ms interventricular delay.

Customer Support: 46-8-474-4756

Brief Summary: Prior to using these devices, please review the Instructions for Use for a complete listing of indications, contraindications, warnings, precautions, potential adverse events and directions for use. Devices depicted may not be available in all countries. Check with your St. Jude Medical representative for product availability in your country. Unless otherwise noted, ™ indicates that the name is a trademark of, or licensed to, St. Jude Medical or one of its subsidiaries. ST. JUDE MEDICAL, the nine-squares symbol and MORE CONTROL. LESS RISK. are registered and unregistered trademarks and service marks of St. Jude Medical, Inc. and its related companies. ©2011 St. Jude Medical, Inc. All rights reserved.

Item GMC8RM768EN